

How to Convert DC450 to Use Monitors with Width Between 25" and 28"



1. Remove the thumb nuts from the outer two bolts of the left-side monitor bracket.
2. Remove the two outer bolts which should now be loose.
3. Loosen the inner two nuts and bolts of the left-side monitor.
4. Slide the monitor bracket to the left, as far as possible.
5. Reinsert the two bolts through the bracket and into the steel plate.
6. While holding the bracket as far left as possible, tighten the thumb nuts on all four bolts.
7. Important: The nuts must be very tight. Use the hex key and a wrench if you do not have a strong grip.
8. Repeat for the right-side bracket.

