



## 1808 LED Fixture

Part Number: 11808\*



## **△ WARNING**

- All wiring should comply with the National Electrical Code and be installed by a qualified electrician
- Minimum 90°C supply conductors
- Sealing of wire openings is necessary to prevent condensation from forming and water collecting inside of fixture. Failure to properly seal fixture will VOID warranty

## **DIRECTIONS**

- 1. Mount junction box, run supply wires, and make wiring connections to power supply
- 2. Seal conduit openings around wires and hole plugs
- Line up the gasket opening with the connector on the lens housing. Insert screws (Qty. 4) through housing and into gasket. This will hold screws during final assembly.

## **SPECIFICATIONS**

Frequency: 50/60 HzPower Factor: >0.9

*Part No.	Description	Qty./ Carton	Wgt./ Carton
1180800A100	LED Fixture, 12 W, VP, 120 V	12	2.1 lb (0.95 kg)
1180800A200	LED Fixture, 14 W, VP, 240 V	12	2.1 lb (0.95 kg)
91808000357	Tamper-Resistant Screw Kit		
918080A1588	12 W, 120 V, Replacement Module		













