

Drop In Replacement Ice Machine Pumps

Hartell ice machine replacement pumps are engineered for quick and hassle-free installation.

Model No: HRIM-1-115 Part No: 803599

Directly Replaces:
GPP-5SC-1A
GPP-5SC-1B
GPP-5SC-1C



Model No: HRIM-2-115 Part No: 803600

Directly Replaces:
GPP-5SC-1



Model No: HRIM-3-120 Part No: 803601

Directly Replaces:
GPPS-1SC-1



Model No: HRIM-4-230 Part No: 803602

Directly Replaces:
GPP-5SC-4A
GPP-5SC-4C
GPP-5SC-4B



Model No: HRIM-8-230 Part No: 803606

Directly Replaces:
GPP-6SC-4FS



Model No: HRIM-10-115 Part No: 803608

Directly Replaces:
GPP-4SC-1FSB
GPP-6SC-1FS



Model No: HRIM-12-230 Part No: 803610

Directly Replaces:
GPP-5SC-4B



Model No: HRIM-14-115 Part No: 803612

Directly Replaces:
GPP-4S-1



Model No: HRIM-16-230 Part No: 803614

Directly Replaces:
GPPS-2SC-2



Model No: HRIM-21-115 Part No: 803619

Directly Replaces:
GPP-1MH-1P



Model No: HRIM-22-230 Part No: 803620

Directly Replaces:
GPP-1MH-2P
GPP-3MH-2P
GPP-4MH-2P
GPP-3MH-2P6



Model No: HRIM-26-115 Part No: 803624

Directly Replaces:
GPP-1MH-1P (3PIN)



Model No: HRIM-29-230 Part No: 803627

Directly Replaces:
GPP-1MH-2P (3PIN)
GPP-3MH-2P (3PIN)
GPP-4MH-2P (3PIN)
GPP-3MH-2P6 (3PIN)



Drop In Replacement Ice Machine Pumps

- Direct-drop-in design fits seamlessly into existing ice machine
- Plug-and-play simplicity
- Time-saving convenience

Item#	Model #	Replaces	Voltage Frequency	Power Watts (W)	Current (A)	HP	Flow Rate GMP	Max Pressure	Pumping Head (Feet)	INLET	OUTLET
803599	HRIM-1-115	12-2919-01/GPP-5SC-1A 12-2920-01/GPP-5SC-1B 12-2920-04/GPP-5C-1C	115v 50/60Hz	98	0.852	0.131	7	3.46	8	OPEN BOTTOM	5/8" BARBED
803600	HRIM-2-115	12-2986-01/GPP-5SC-1	115v 50/60Hz	48	0.852	0.064	1.8	4.33	10	BOTTOM FILTERED	1/2" BARBED
803601	HRIM-3-120	12-2293-02/GPPS-1SC-1	115v 50/60Hz	48	0.417	0.064	3	4.33	10	1/2" Barbed	1/2" Barbed, Overflow, 1/2" Barbed
803602	HRIM-4-230	12-2919-02/GPP-5SC-4A 12-2920-02/GPP-5SC-4C 12-2920-03/GPP-5SC-4B	208-230v 50/60Hz	70	0.304	0.094	6	2.60	6	OPEN BOTTOM	5/8" Barbed
803606	HRIM-8-230	12-2714-01/GPP-6SC-4FS	208-230v 50/60Hz	112	0.487	0.150	12	5.19	12	OPEN BOTTOM	3/4" Barbed
803608	HRIM-10-115	12-2586-04/GPP-4SC-1FSB 12-2714-02/GPP-6SC-1FS 12-2856-01 / GPP-4SC-1FSA (will need 5/8" adaptor)	115v 50/60Hz	175	1.522	0.094	12	5.19	12	OPEN BOTTOM	3/4" Barbed
803610	HRIM-12-230	12-2920-05/GPP-5SC-4B	208-230v 50/60Hz	95	0.413	0.127	6	2.16	5	OPEN BOTTOM	5/8" Barbed
803612	HRIM-14-115	12-2265-01/GPP-4S-1	115v 60Hz	98	0.852	0.131	7	3.46	8	OPEN BOTTOM	5/8" Barbed
803614	HRIM-16-230	12-2256-02/GPPS-2SC-2	208-230v 50/60Hz	125	0.543	0.168	15	6.93	16	1" Straight	1" Straight, Overflow 3/4" Straight
803619	HRIM-21-115	9161076-01/GPP-1MH-1P	115v 50/60Hz	30	0.261	0.040	4	1.30	3	OPEN BOTTOM	5/8" BARBED
803620	HRIM-22-230	9161076-02/GPP-1MH-2P 9161079-02/GPP-3MH-2P 9161079-03/GPP-4MH-2P 9161079-06/GPP-3MH-2P6	208-230v 50/60Hz	36	0.157	0.127	4	1.73	4	OPEN BOTTOM	5/8" BARBED
803624	HRIM-26-115	9161137-01 GPP-1MH-1P (3PIN)	115v 50/60Hz	30	0.261	0.040	4	1.73	4	OPEN BOTTOM	5/8" Barbed
803627	HRIM-29-230	9161137-02/GPP-1MH-2P (3PIN) 9161138-01/GPP-4MH-2P (3PIN) 9161138-02/GPP-3MH-2P (3PIN)	208-230v 50/60Hz	70	0.304	0.094	9	3.90	9	OPEN BOTTOM	5/8" Barbed